

ENERSYS 12V LEAD ACID BATTERIES

UPS/SPS SYSTEMS, EMERGENCY LIGHTING, ALARM SYSTEMS

Part Number	Volts	Capacity 20Hr. Rate	Dimensions (Inches)			Weight (Lbs)	Cross Reference	Terminations
			Length	Width	Height Inc. Term			
LEAD-12-0.8	12	0.8	3.78	0.98	2.42	.77	NP0.8-12	WIRE & CONNECTOR
LEAD-12-1.2	12	1.2	3.82	1.89	2.15	1.25	NP1.2-12	.187 TAB
LEAD-12-1.3HRD	12	1.3	5.28	2.64	2.52	3.09	NPH 1.3-12	.187 TAB
LEAD-12-2	12	2.0	5.91	.79	3.50	1.54	NP2-12	.187 TAB SIDE
LEAD-12-2HRD	12	2.0	2.68	2.01	3.46	1.85	NPH2-12	.187 TAB
LEAD-12-2HRDFR	12	2.0	2.68	2.01	3.46	1.85	NPH2-12FR	.187 TAB
LEAD-12-2.3	12	2.3	7.01	1.34	2.52	2.07	NP2.3-12, NP 1.9-12	.187 TAB
LEAD-12-2.3HRD	12	2.3	7.01	1.34	2.52	2.05	NPH2.3-12	.187 TAB
LEAD-12-2.3HRDFR12	12	2.3	7.01	1.34	2.52	2.05	NPH2.3-12FR	.187 TAB
LEAD-12-2.6	12	2.6	5.28	2.64	2.52	2.47	NP2.6-12	.187 TAB
LEAD-12-3.2HRD	12	3.2	5.28	2.64	2.52	3.09	NPH3.2-12	.187 TAB
LEAD-12-4	12	4.0	3.54	2.76	4.17	3.74	NP4-12,JC1240	.187 TAB
LEAD-12-5	12	5.0	3.54	2.76	4.17	4.41	NP5-12	.187 TAB
LEAD-12-5HRD			USE LEAD-NPX25				NPH5-12	
LEAD-12-5HRDFR			USE LEAD-NPX25FR				NPH5-12FR	
LEAD-12-7	12	7.0	5.94	2.56	3.84	6.17	NP7-12	.187 TAB
LEAD-12-7FR	12	7.0	5.94	2.56	3.84	6.17	NP7-12FR	.187 TAB
LEAD-12-7-250	12	7.0	5.94	2.56	3.84	6.17	NP7-12-250	.250 TAB
LEAD-12-8.5			USE LEAD-NPX35					
LEAD-12-8.5FR			USE LEAD-NPX35FR					
LEAD-12-12	12	12.0	5.94	3.86	3.84	8.82	NP12-12	.250 TAB
LEAD-12-12FR	12	12.0	5.94	3.86	3.84	8.82	NP12-12FR	.250 TAB
LEAD-12-18	12	18.0	7.13	2.99	6.57	13.70	NPG-18-12, NP18-12B	NUT & BOLT
LEAD-12-18FR	12	18.0	7.13	2.99	6.57	13.70	NP-18-12FR,	NUT & BOLT
LEAD-12-20			USE LEAD-NPX80					
LEAD-12-20FR			USE LEAD-NPX80FR					
LEAD-12-24B	12	24.0	6.54	6.89	4.92	19.10	NP24-12B	NUT & BOLT
LEAD-12-24B-FR	12	24.0	6.54	6.89	4.92	19.10	NP24-12BFR	NUT & BOLT
LEAD-12-24T	12	24.0	6.54	6.89	4.92	19.10	NP24-12	.250 TAB
LEAD-12-24T-FR	12	24.0	6.54	6.89	4.92	19.10	NP24-12FR	.250 TAB
LEAD-12-26B	12	26.0	6.54	4.92	6.89	20.50	NP26-12B	NUT & BOLT
LEAD-12-26R	12	26.0	6.54	4.92	6.89	20.50	NP26-12R	RECEPTACLE
LEAD-12-28B			USE LEAD-NPX100B					
LEAD-12-28R			USE LEAD-NPX100R					
LEAD-12-33	12	33.0	7.68	5.19	7.15	26.5	U1 VIPER 33-12, VPU133-12	NUT & BOLT
LEAD-12-38	12	38.0	7.74	6.50	6.89	30.40	NP38-12, NP38-12B	NUT & BOLT
LEAD-12-40B			USE LEAD-NPX150B					
LEAD-12-40R			USE LEAD-NPX150R					
LEAD-12-55	12	57.0	10.16	6.73	8.82	39.5	DM55-12	NUT & BOLT
LEAD-12-65	12	65.0	13.78	6.53	6.85	50.20	NP65-12	NUT & BOLT
LEAD-12-80	12	73.0	12.05	6.81	9.09	46.3	DM80-12	NUT & BOLT

NPX SERIES

LEAD-NPX25	12	5.0	3.54	2.75	4.17	4.41	NPX-25	23 W/CELL	.250 TAB
LEAD-NPX25FR	12	5.0	3.54	2.75	4.17	4.41	NPX-25FR	23 W/CELL	.250 TAB
LEAD-NPX35	12	8.5	5.94	2.56	3.84	6.24	NPX-35	35 W/CELL	.187 TAB
LEAD-NPX35FR	12	8.5	5.94	2.56	3.84	6.24	NPX-35FR	35 W/CELL	.187 TAB
LEAD-NPX80B	12	20.0	7.13	2.99	6.57	14.50	NPX-80	80 W/CELL	NUT & BOLT
LEAD-NPX80FR	12	20.0	7.13	2.99	6.57	14.50	NPX-80FR	80 W/CELL	NUT & BOLT
LEAD-NPX100B	12	28.0	6.54	4.92	6.89	20.80	NPX-100B	95 W/CELL	NUT & BOLT
LEAD-NPX100R	12	28.0	6.54	4.92	6.89	20.80	NPX-100R	95 W/CELL	RECEPTACLE
LEAD-NPX150B	12	40.0	7.76	6.50	6.89	34.10	NPX-150B	150 W/CELL	NUT & BOLT
LEAD-NPX150R	12	40.0	7.76	6.50	6.89	34.10	NPX-150R	150 W/CELL	RECEPTACLE

HRD = HIGH RATE DISCHARGE / FR = FLAME RETARDANT / R = RECEPTACLE

LEAD ACID